Computer Physics Communications 58 (1990) 119-125 North-Holland

MERLIN-2.1 DOUBLE PRECISION

D.G. PAPAGEORGIOU¹ and I.E. LAGARIS¹

Physics dept., University of Ioannina, P.O. Box 1186, Ioannina 45110, Greece

Received 8 August 1989

MERLIN-2.1 is an adaptation of the MERLIN-2.0 package, mainly designed to run on computers using 32-bit floating point arithmetic. The standard Merlin-2.0 on such machines, achieves a precision of 7 significant digits at most. This is insufficient since in many real problems a higher precision is required. MERLIN-2.1 treats this inadequacy using double precision operations, enhancing so the precision up to about 14 significant digits, in the standard user-friendly Merlin environment.

ADAPTATION SUMMARY

Title of adaptation: MERLIN-2.1 DOUBLE PRECISION

Adaption number: 0001

Program obtainable from: CPC Program Library, Queen's University of Belfast, N. Ireland (see application form in this issue)

Reference to original program: Title: MERLIN-2.0 – enhanced and programmable version; Cat.no: ABHB; Ref. in CPC: 52 (1989) 241

Authors of original program: D.G. Papageorgiou, C.S. Chassapis and I.E. Lagaris

Computer for which the adaptation is designed and others on which it is operable: the adaptation is mainly designed for computers using 32-bit floating point numbers, but it will work on any machine equally well, since all changes are in ANSI Fortran 77

Computer: VAX 8350; Installation: INFN, Sezione di Pisa, University of Pisa, Italy

Operating system: VMS 5.1

High speed storage required: depending upon the maximum number of variables the object can handle (47000 words for 30 variables, 90000 words for 150 variables).

No. of bits in a word: 32

No. of lines required to effect adaptation: not applicable; a new source code is provided with a total of 7502 lines

¹ E-Mail: Merlin @ GRIOANUN.BITNET

0010-4655/90/\$03.50 © Elsevier Science Publishers B.V. (North-Holland)

Nature of physical problem

A lot of problems in physics, chemistry, applied mathematics as well as in engineering and in other fields, are quite often reduced to minimizing a function of several variables. MERLIN-2.1 is a programmable system designed to minimize a multi-dimensional function.

Method of solution

Six algorithms are implemented. Three of them make use of the function's gradient and hence are suitable for minimizing differentiable functions, the other three do not use derivatives at all and so are applicable to non-differentiable functions as well [2].

Reasons for the adaptation

The insufficient precision (7 significant digits) obtained when running on computers with a word of about 32 bits.

Restrictions on the complexity of the problem

Currently MERLIN is dimensioned to handle up to 150 variables. However, by redimensioning a few arrays it can easily be enhanced or reduced according to the user's needs, as described in the provided manual of the original program.

Typical running time

Heavily depending on the complexity of the objective function. Note that since all the calculations use double precision arithmetic, this version of the program is slower than the original release [1,2]. The test run took 6.30 cpu seconds on a VAX 8350 under VMS 5.1.

References

- D.G. Papageorgiou, C.S. Chassapis and I.E. Lagaris, Comput. Phys. Commun. 52 (1989) 241.
- [2] G.A. Evangelakis, J.P. Rizos, I.E. Lagaris and I.N. Demetropoulos, Comput. Phys. Commun. 46 (1987) 401.

LONG WRITE-UP

1. Introduction

MERLIN is an optimization package, that has been proved very effective in lots of problems, in physics, chemistry, engineering, etc. Both, its original release [1] and the programmable version [2], are written in ANSI Fortran 77, using single precision arithmetic. When using the program in a computer with 32-bit floating point numbers, the seven significant digits offered, may prove insufficient in some cases where increased precision is required. This version of the program cures the problem, offering double precision operations. Note that, since this version is also written in ANSI Fortran 77, one may use it in a computer with 64-bit floating point numbers, to increase the number of significant digits to about 28.

2. Detailed description

The following paragraphs describe the changes made to the program of ref. [2] and discuss how the user written part (FUNMIN, GRANAL, MASTER) should be. It is assumed that the reader is familiar with the MERLIN package as described in refs. [1,2].

2.1. Double precision variables

In order to achieve increased accuracy, we converted all single precision variables to double precision. This was done by means of the following implicit statement that was added in almost every subprogram:

IMPLICIT DOUBLE PRECISION (A-H,O-Z)

In addition we replaced all intrinsic functions with their generic names and all function subprograms were declared as DOUBLE PRECISION functions. We also converted every real constant to the D-exponent representation. E.g 5.0 is now written as 5.0D0.

2.2. The objective function FUNMIN

The user written objective function, namely FUNMIN, should be in double precision. There is

no point having the program to operate in double precision, while FUNMIN performs the function evaluation in single. A typical FUNMIN declaration should be like:

DOUBLE PRECISION FUNCTION FUNMIN (X,N) IMPLICIT DOUBLE PRECISION (A-H,O-Z) DIMENSION X(N)

2.3. Derivative calculation by GRANAL

If you decide to use your own derivative code, you must supply the GRANAL subroutine as described in ref. [1]. All the derivatives should be calculated using double precision. A typical GRANAL declaration should be like:

SUBROUTINE GRANAL(N,X,VAL,GRAD) IMPLICIT DOUBLE PRECISION(A-H,O-Z) DIMENSION X(N),GRAD(N)

2.4. The main program

MERLIN is called as a subroutine, and the user may want to write his own main program to do this. The call now involves double precision variables and should be of the form:

PARAMETER (NMAX = 30, NMAXW = NMAX**2 + NMAX) DOUBLE PRECISION VERSIM(NMAXW) ...

CALL MERLIN(N, VERSIM, NMAXW, IQUIT)

2.5. The input-output units

The unit numbers assigned to the standard input and output (defined in the Block Data EQUIP) have been set to 5 and 6, correspondingly; these unit numbers are used by many machines for interactive I/O. To run the program in batch mode, just change these values to the desired ones, or use the appropriate operating system command to assign these units to your input/output files.

2.6. The random number generator

The random number generator (used in subroutine RANDOM) is the only non-standard part of the program and will work only in VAX/VMS machines. You should replace the call to RAN with your local random number generator. The value returned must be uniformly distributed in (0,1).

2.7. The macro editor

MEDIT, the macro editor has been modified. No command other than E (Exit) and I (Insert) is allowed when the macro file is empty. (See the Merlin User's guide of ref. [1]) When using MEDIT to modify a line of the macro file, the incorrect line is printed on the screen and the user enters modification characters, below. These characters are input from the terminal, by a Fortran READ statement. This process has been proved to be non-portable, since some systems issue a prompt when reading data from a terminal, while others do not. A parameter (named INDENT) has been added to SUBROUTINE MODIFY, to control

Table 1 Objective function

```
DOUBLE PRECISION FUNCTION FUNMIN(X,N)
IMPLICIT DOUBLE PRECISION (A-H,O-Z)
DIMENSION X(N)
X1 = X(1)
X2 = X(2)
X3 = X(3)
FUNMIN = (X1 - 3) * * 2 + 5 * X2 * * 2 * (X3 - X1) * * 4 + 10 * X3 * * 2 * (100 - X1 * X3) * * 2
RETURN
END
SUBROUTINE GRANAL (N.X.VAL.GRAD)
IMPLICIT DOUBLE PRECISION (A-H,O-Z)
DIMENSION X(N), GRAD(N)
X1 = X(1)
X2 = X(2)
X3 = X(3)
GRAD(1) = 2 * (X1 - 3) - 20 * X2 * * 2 * (X3 - X1) * * 3 - 20 * X3 * * 3 * (100 - X1 * X3)
GRAD(2) = 10 * X2 * (X3 - X1) * *4
GRAD(3) = 20 * X2 * * 2 * (X3 - X1) * * 3 + 20 * X3 * (100 - X1 * X3) * * 2
            -20 * X3 * *2 * X1 * (100 - X1 * X3)
RETURN
END
```

the positioning of the incorrect line during the modification process. You must set this parameter to the number of characters printed on the screen as prompt, by your local system. Currently this parameter is set to 0, implying that no prompt is printed during a Fortran READ.

2.8. A note on MCL

MCL is the programming language developed to drive MERLIN and help the user construct efficient minimization strategies [3]. The new version, MERLIN-2.1 presented here, is absolutely compatible with the object code generated by the MCL compiler. (The compiler itself does not need to be modified to handle double precision operations)

2.9. Other improvements

Several parts of the program have been improved in order to make it respond in a more friendly manner. Subroutine CHANGE has been modified to handle blank lines and incorrect input indices in a better way. Function FACT is now written so as to allow factorials to be calculated within the accuracy of the particular machine. A parameter (which currently is set to 100, but may assumed any desired value) controls the range of the factorials. Subroutine DETUNT will now consider only units numbers in between 1 and 99.

3. Test run description

The objective function (listed in table 1) is the same as in refs. [1,2], written, however, in double precision. The input deck should reside in file

FOR005.DAT, while the output is contained in the file FOR006.DAT. The test run took 6.30 CPU seconds on a VAX 8350.

References

- D.G. Papageorgiou, C.S. Chassapis and I.E. Lagaris, Comput. Phys. Commun. 52 (1989) 241.
- [2] G.A. Evangelakis, J.P. Rizos, I.E. Lagaris and I.N. Demetropoulos, Comput. Phys. Commun. 46 (1987) 401.
- [3] C.S. Chassapis, D.G. Papageorgiou and I.E. Lagaris, Comput. Phys. Commun. 52 (1989) 223.

TEST RUN INPUT

```
3
IRF
POINT
1 30 2 30 3 33.88
Λ
GODFATHER
х
Ŷ
z
SHORTDIS
ROLL
5 0 1 800 2 0
SHORTDIS
SINPLEX
5 2000 6 0
SHORTDIS
BFGS
1 2000 6 0
DFP
 1 2000 6 0
SHORTDIS
STOP
```

TEST RUN OUTPUT

ENTER . OF VARIABLES _____ NERLIN-2.1 DOUBLE PRECISION VERSION ADAPTED BY : D.G. PAPAGEORGIOU & I.E. LAGARIS PHYSICS DEPARTMENT UNIVERSITY OF IOANNINA P.O.BOX 1186 10ANNINA - G R E E C E , 45110 M E R L I N 2.1 (DOUBLE PRECISION) IOANNINA, AUGUST - 1989 _____ TO OBTAIN ON-LINE INFORMATION, MAKE SURE THAT FILE: HELP , IS PRESENT ESTIMATED MACHINE'S ACCURACY: 0.10E-14 ... ENTER PROCESSING MODE OPTION. (BATCH / IAF) WAAHING MEALIN MMMMMIS AT YOUR CONHAND III POINT POINT /\/\/\/\/ HERLIN IS AT YOUR COMMAND !!! GODFATHER VARIABLE 1 : VARIABLE 2: VARIABLE 3 : 1) X 2) Y 3) Z

 $\Lambda \Lambda \Lambda \Lambda \Lambda$ MEALIN IS AT YOUR COMMAND I!! SHORTDIS TOTAL HU. OF CALLS -HU. OF CALLS SINCE LAST RESET 1
 1) X
 30.00000000000

 2) Y
 30.00000000000

 3) Z
 33.88000000000
 3) Z VALUE..... ///////// MERLIN IS AT YOUR COMMAND !!! ROLL -----ROLL - PANEL ------_____ INDEXDESCRIPTIONVALUEMENU1)NUMBER OF CALLS300ANY INTEGER2)TOLERANCE0.100E-02ANY REAL IN (0,1)3)STEP FACTOR0.30E+01ANY REAL > 14)FAILURES ALLONED4ANY INTEGER5)PRINTOUT SELECTION10/1/26)HALL-PARAMETER3ANY INTEGER7)CARCEL-BUTTON1(0/1/2) _____ ENTER CHANGES ALL VARIABLES FIXED ALL VARIABLES FIXED ALL VARIABLES FIXED HUMBER OF ROLL CALLS: 224 /\/\/\/\/\/\ HERLIN IS AT YOUR COMMAND III SHORTDIS Total Hu. of Calls = 225 NU. OF CALLS SINCE LAST RESET 225 /\/\/\/\/\/ NERLIN IS AT YOUR CONMAND III SIMPLEX _____ SINPLEX - PAHEL VALUE MENU 1 (1/2) INDEX DESCRIPTION
 HDEX
 DESCRIPTION
 URLUE
 MEHU

 1)
 INITIALIZATION SCHEME
 1
 (1/2)

 (SYSTEMATIC/RANDON)
 1
 1
 (1/2)

 2)
 INITIALIZATION TOLERANCE
 0.100
 ANY REAL

 3)
 INIT. CALLS/URRIABLE
 100
 ANY INTEGER

 4)
 SINPLEX TOLERANCE
 0.000E+00
 ANY REAL

 5)
 SIMPLEX CALLS
 500
 ANY INTEGER

 6)
 PRINTOUT SELECTION
 1
 (0/1/2)

 7)
 CRHCEL-BUTTON
 1
 (0/1/2)
 _____ ENTER CHANGES HUMBER OF SIMPLEX CALLS: 2028 /\/\//\// MERLIN IS AT YOUR COMMAND !!! SHORTDIS TOTAL HU. OF CALLS -2253 NU. OF CALLS SINCE LAST RESET 2253
 1) X
 3.0000000000000

 2) Y
 0.40658440073078-133

 3) Z
 0.58722944820820-135

 URLUE.....
 0.16838565116755-264

ALL UARIABLES FIXED ALL UARIABLES FIXED ALL UARIABLES FIXED AUDBER OF BFOS CALLS: 18 ////////////////////////////////////	IHDEX 1) N 2) T 3) E 4) U 5) U 6) P 7) H 8) C ENTER H ILL VARIA ILL VARIA ILL VARIA ILL VARIA ILL VARIA 1LL VARIA 1.1 T 3.1 E 4.1 L 5.1 U 6.2 T 7.1 H <	DESCRIPTION UNBER OF CALLS OLERANCE AROR-BOUND SE/RECALCULATE GRADI SE/RESET HESSIAN RINTOUT SELECTION ALL-PARAMETER ANCEL-BUTTON CHANGES BLES FIXED BLES FIXED BLES FIXED BLES FIXED IUNBER OF BFGS V/\//\ MERLIN DESCRIPTION UNBER OF CALLS OLERANCE RAOR-BOUND	CALLS: Is At DFP - PANE	UALUE 300 0.100E-02 0.10E-01 0 1 3 1 1 1 1 8 4 400R COMMAND	HEHU RHY IHTEGER AHY REAL (1 (0,1) RHY REAL (1 (1/0) 0/1/2 RHY IHTEGER (0/1/2).
2) TOLERANCE 0.100E-02 RHY REAL (H (0,1) 3) ERROR-BOUND 0.10E-01 RHY REAL (I (0,1) 3) DERACR-BOUND 0.10E-01 RHY REAL (I (0,1) 4) USE/RECRLCULATE GARDIENT 0 (1/0) 5) USE/RECRLCULATE GARDIENT 0 (1/0) 6) PRINTOUT SELECTION 1 0/1/2 7) UALL-PARAMETER 3 ANY INTEGER 8) CANCEL-BUTTON 1 (0/1/2) ENTER CHANGES RIL UARIABLES FIXED NUMBER OF BFGS CALLS: 18 INTER CHANGES NUMBER OF CALLS: 18 NUMBER OF CALLS: 18 INTER CHANGES NUMBER OF CALLS: 18 INTER CHANGES NUMBER OF CALLS: 300 ANY HATEGER INTER CHANGES NUMBER OF CALLS: 300 NUMBER OF CALLS INTER CHANGES NUMBER OF CALLS INTER CALCULATE GRADIENT 1	1) H 2) T 3) E 4) U 5) U 6) P 7) H 8) C ENTER ILL VARIA ILL VARIA ILL VARIA ILL VARIA 1L VARIA 1.L VARIA 1.L VARIA 1.1 VARIA 1	UNBER OF CALLS OLERANCE AROA-BOUND ISE/RECALCULATE GRADI SE/RESET HESSIAN RINTOUT SELECTION ALL-PARAMETER ANCEL-BUTTON CHANGES BLES FIXED BLES FIXED BLES FIXED BLES FIXED BLES FIXED INMBER OF BFGS V/\//\ MERLIN DESCRIPTION UNBER OF CALLS OLERANCE RAOR-BOUND	CALLS: Is At DFP - Pane	0.100E-02 0.10E-01 0 1 3 1 1 18 Your Command	AMY REAL IN (0,1) RMY REAL < 1 (1/0) (1/0) 0/1/2 AMY INTEGER (0/1/2)
2) TOLERANCE 0.100E-02 RHV REAL (H (0,1) 3) ERROR-BOUND 0.10E-01 RHV REAL (I (0,1) 3) ERROR-BOUND 0.10E-01 RHV REAL (I (0,1) 4) USE/RESET HESSIAN 0 (1/0) 5) USE/RESET HESSIAN 0 (1/0) 6) PRIHTOUT SELECTION 1 0/1/2 7) HALL-PARAMETER 3 RHV INTEGER 8) CANCEL-BUTTON 1 (0/1/2). EHTER CHANGES RUL VARIABLES FIXED ALL VARIABLES FIXED ALL VARIABLES FIXED ALL VARIABLES FIXED ALL VARIABLES FIXED NUMBER OF BFOS CALLS: 10 INTER CHANGES INTER CHANGES INTER CHANGES NUMBER OF CALLS: 10 INTER CHANGES INTER CHANGES INTER CHANGES NUMBER OF CALLS: 10 INTER CHANGES INTER CHANGES INTER CHANGES INTER CHANGES INTER CHANGES </td <td>2) T 3) E 4) L 5) U 6) P 7) W 8) C EHTER ILL VARIA ILL VARIA ILL VARIA ILL VARIA ILL VARIA ILL VARIA 11 H 2) T 3) E 4) L 5) U 6) P 7) W 8) C</td> <td>OLEAANCE AROR-BOUHD SE/RECALCULATE GRADI SE/RESET HESSIAH AINTOUT SELECTION ALL-PARAMETER ANCEL-BUTTON CHANGES BLES FIXED BLES FIXED BLES FIXED BLES FIXED HUMBER OF BFGS V/V//V MERLIN DESCRIPTION UNBER OF CALLS OLEAANCE ROD-BOUHD</td> <td>CALLS: Is At DFP - Pane</td> <td>0.100E-02 0.10E-01 0 1 3 1 1 18 Your Command</td> <td>AMY REAL IN (0,1) RMY REAL < 1 (1/0) (1/0) 0/1/2 AMY INTEGER (0/1/2)</td>	2) T 3) E 4) L 5) U 6) P 7) W 8) C EHTER ILL VARIA ILL VARIA ILL VARIA ILL VARIA ILL VARIA ILL VARIA 11 H 2) T 3) E 4) L 5) U 6) P 7) W 8) C	OLEAANCE AROR-BOUHD SE/RECALCULATE GRADI SE/RESET HESSIAH AINTOUT SELECTION ALL-PARAMETER ANCEL-BUTTON CHANGES BLES FIXED BLES FIXED BLES FIXED BLES FIXED HUMBER OF BFGS V/V//V MERLIN DESCRIPTION UNBER OF CALLS OLEAANCE ROD-BOUHD	CALLS: Is At DFP - Pane	0.100E-02 0.10E-01 0 1 3 1 1 18 Your Command	AMY REAL IN (0,1) RMY REAL < 1 (1/0) (1/0) 0/1/2 AMY INTEGER (0/1/2)
5) USC/RESET HESSIAN 0 (1/0) 6) PRIHTOUT SELECTION 1 0/1/2 7) HALL-PARAMETER 3 ANY INTEGER 8) CANCEL-BUTTON 1 (0/1/2) ENTER CHANGES ILL UARIABLES FIXED INDEP - PANEL INDEX INDER OF CALLS INDER OF CALLS INDER OF CALLS INDER OF CALLS INDEC CONTAND INDEC CONTAND INDEX INDEX INDEX INDEX <td>3) E 4) U 5) U 6) V 7) W 8) C ENTER ILL VARIA ILL VARIA ILL VARIA ILL VARIA 1LL VARIA 1L VARIA 1L VARIA 11 VARIA 12 VARIA 13 E 4) U 5) U 6) V 7) W 8) C</td> <td>AROA-BOUHD SE/RECALCULATE GRADI SE/RESET HESSIAH RINTOUT SELECTIOH ALL-PARAMETER ANCEL-BUTTOH CHANGES BLES FIXED BLES FIXED BLES FIXED BLES FIXED BLES FIXED UNBER OF BFGS V/\//\ MERLIN DESCRIPTION UNBER OF CALLS OLEAANCE RAOR-BOUHD</td> <td>CALLS: Is At DFP - Pane</td> <td>0 1 3 1 18 40ur command </td> <td>(1/0) 0/1/2 RHY HHTEGER (0/1/2) .</td>	3) E 4) U 5) U 6) V 7) W 8) C ENTER ILL VARIA ILL VARIA ILL VARIA ILL VARIA 1LL VARIA 1L VARIA 1L VARIA 11 VARIA 12 VARIA 13 E 4) U 5) U 6) V 7) W 8) C	AROA-BOUHD SE/RECALCULATE GRADI SE/RESET HESSIAH RINTOUT SELECTIOH ALL-PARAMETER ANCEL-BUTTOH CHANGES BLES FIXED BLES FIXED BLES FIXED BLES FIXED BLES FIXED UNBER OF BFGS V/\//\ MERLIN DESCRIPTION UNBER OF CALLS OLEAANCE RAOR-BOUHD	CALLS: Is At DFP - Pane	0 1 3 1 18 40ur command 	(1/0) 0/1/2 RHY HHTEGER (0/1/2) .
5) USC/RESET HESSIAH 0 (1/0) 6) PRINTOUT SELECTION 1 0/1/2 7) HALL-PRARMETER 3 AHY INTEGER 8) CANCEL-BUTTOM 1 (0/1/2) ENTER CHANGES ILL UARIABLES FIXED INDEP - PANEL INDER INDER INDER INDER INDER ILL UARIABLES FIXED INDER INDER INDER INDER INDEC INDEC	4) L 5) U 6) P 7) U 8) C EHTER ILL VARIA ILL VARIA ILL VARIA ILL VARIA Y//// FP 	ISE/RECALCULATE GRADI SE/RESET HESSIAN RINTOUT SELECTION ALL-PARAMETER ANCEL-BUTTON CHANGES BLES FIXED BLES FIXED BLES FIXED BLES FIXED BLES FIXED IUMBER OF BFGS V///// MERLIN DESCRIPTION UNBER OF CALLS OLERANCE RAGN-BOUND	CALLS: Is At DFP - Pane	0 1 3 1 18 40ur command 	(1/0) 0/1/2 RHY HHTEGER (0/1/2) .
5) USE/RESET HESSIAH 0 (1/0) 6) PRINTOUT SELECTION 1 0/1/2 7) HALL-PARAMETER 3 AHY INTEGER 8) CANCEL-BUTTOM 1 (0/1/2) ENTER CHANGES ILL VARIABLES FIXED INTER COLSPANE INTER COLSPANE INTER OF CALLS INTER OF CALLS INTER COLSPANE <	5) U 6) P 7) H 8) C ENTER ILL VARIA ILL VARIA ILL VARIA 1 VARIA 1 FP 	SE/RESET HESSIAN RINTOUT SELECTION ALL-PARAMETER ANCEL-BUTTON CHANGES BLES FIXED BLES FIXED BLES FIXED BLES FIXED UMBER OF BFGS \/\//\ MERLIN DESCRIPTION UMBER OF CALLS OLEARNCE RAOR-BOUND	CALLS: Is At DFP - Pane	0 1 3 1 18 40ur command 	(1/0) 0/1/2 RHY HHTEGER (0/1/2) .
6) PRINTOUT SELECTION I 0/1/2 7) WALL-PARAMETER 3 AHV INTEGER 8) CANCEL-BUTTOH I (0/1/2) ENTER CHANGES LL VARIABLES FIXED LL VARIABLES FIXED LL VARIABLES FIXED LL VARIABLES FIXED LL VARIABLES FIXED LL VARIABLES FIXED HUMBER OF BFOS CALLS: 18 ////////////////////////////////////	6) P 7) U 8) C EHTER LL VARIA LL VARIA LL VARIA LL VARIA /\/// FP /\//// FP /\/// FP /\/// FP /\/// FP /\/// FP /\/// FP /\/// FP /\/// FP /\/// FP /\/// FP /\/// FP /\/// FP /\/// FP /\/// FP /\/// FP /\/// FP /\/// FP /\/// FP /\/// FD /\/// FD /\/// FD /\/// FD /\/// FD /\/// FD /\/// FD /\/// FD /\/// FD /\/// FD /\/// FD /\/// FD /\/// FD /\/// FD /\/// FD /\/// FD /\/// FD /\/// FD /\/// FD /\// FD /\/// FD /\// FD /\/// FD /\/// FD /\/// FD /\/// FD /\/// FD /\/// FD /\/// FD /\/// FD /\/// FD /\/// FD /\/// FD /\/// FD /\/// FD /\/// FD /\//// FD /\/// FD /\/// FD /\/// FD /\/// FD ///// FD ///// FD //////////	RINTOUT SELECTION ALL-PARAMETER ANCEL-BUTTON CHANGES BLES FIXED BLES FIXED BLES FIXED BLES FIXED IUMBER OF BFGS \/\//\ MERLIN DESCRIPTION UNBER OF CALLS OLEARNCE RAOR-BOUND	CALLS: Is at DFP - Pane	1 3 1 18 Your Command 	0/1/2 RHY IHTEGER (0/1/2) .
7) UALL-PARAMETER 3 ANV INTEGER 8) CANCEL-BUTTON 1 (0/1/2) ENTER CHANGES LL UARIABLES FIXED LU UARIABLES FIXED LU UARIABLES FIXED LIL UARIABLES FIXED LIL UARIABLES FIXED LIL UARIABLES FIXED LIL UARIABLES FIXED ILL UARIABLES FIXED INTOR MURBER OF BFOS CALLS: 18 ///////////////////////////////////	7) W 8) C EHTER ILL VARIA ILL VARIA ILL VARIA ILL VARIA /\/// FP /\/// FP IHDEX 1) H 2) T 3) E 4) L 5) U 6) P 7) W 8) C	ALL-PARAMETER AHCEL-BUTTOM CHANGES BLES FIXED BLES FIXED BLES FIXED IUMBER OF BFGS \/\///\ MERLIN DESCRIPTION UNBER OF CALLS OLEARNCE RAGN-BOUND	CALLS: Is at DFP - Pane	3 1 18 Your Command .L	ANY INTEGEA (0/1/2) .
8) CRNCEL-BUTTON 1 (0/1/2) ENTER CHANGES ILL UARIABLES FIXED NUMBER OF BFOS CALLS: INDEX DESCRIPTION UARIABLES OFP - PAMEL DFP - PAMEL INDER OF CALLS 300 ANY INTEGER 2) TOLERANCE 0.100E-02 ANY REAL IN (0,1) 3) ERROR-BOUND 0.100E-01 ANY REAL IN (0,1) 4) USE/RESET HESSIAN 1 1) USE/RESET HESSIAN 1 1) USE/RESET HESSIAN 1 1) UAL-PARAMETER 3 3) CANCEL-BUTTON 1 1) UARIABLES FIXED NURBER OF DFP CALLS: 0 ////////////////////////////////////	8) C ENTER ILL ILL UARIA INDEX 1) INDEX 1) 3) E 4) L 5) U 6) P 7) N 8) C	AHCEL-BUTTOH CHANGES BLES FIXED BLES FIXED BLES FIXED IUMBER OF BFGS \/\/\/\ MERLIN Description Umber of Calls Olearance Bron-Bound	CALLS: Is at DFP - Pane	1 	(0/1/2)
ENTER CHANGES ILL UARIABLES FIXED ILL UARIABLES FIXED HUNBER OF BFOS CALLS: 18 ////////////////////////////////////	ILL UARIA ILL UARIA ILL UARIA ILL UARIA /\/// FP INDEX I) H 2) T 3) E +) L 5) U 6) P 7) H 8) C	CHANGES BLES FIXED BLES FIXED BLES FIXED UNBER OF BFGS \/\//\ MERLIN DESCRIPTION UNBER OF CALLS OLEAANCE RAOR-BOUND	CALLS: Is at DFP - Pane	18 Your Command .L	
ILL UARIABLES FIXED ILL UARIABLES FIXED HUMBER OF BFOS CRLLS: 18 /\/\/\/\/\/ MERLIN IS AT YOUR CONMAND !!! FP DFP - PANEL INDEX INDEX DFP - PANEL INDEX INDEX DFP - PANEL INDEX INDEX INDEX DFP - PANEL INDEX INDEX<	ILL UARIA ILL UARIA ILL UARIA Y//// FP IHDEX 1) H 2) T 3) E 4) L 5) U 6) U 7) H 8) C	BLES FIXED BLES FIXED BLES FIXED IUNBER OF BFGS \/\/// MERLIN DESCRIPTION UNBER OF CALLS OLEARANCE RAGN-BOUND	IS AT DFP - Pane	YOUR COMMAND	
LL UARIABLES FIXED LL UARIABLES FIXED HUMBER OF BFGS CALLS: 18 ////////////////////////////////////	LL UARIA LL UARIA FP 	BLES FIXED BLES FIXED IUMBER OF BFGS \/\/\/\ MERLIN 	IS AT DFP - Pane	YOUR COMMAND	
LL UARIABLES FIXED LL UARIABLES FIXED HUMBER OF BFGS CALLS: 18 ////////////////////////////////////	LL UARIA LL UARIA FP 	BLES FIXED BLES FIXED IUMBER OF BFGS \/\/\/\ MERLIN 	IS AT DFP - Pane	YOUR COMMAND	
LL URRIABLES FIXED HUMBER OF BFGS CALLS: 18 ////////////////////////////////////	LL UARIA ///// FP INDEX 1) H 2) T 3) E 4) L 5) U 6) V 7) H 8) C	BLES FIXED IUNBER OF BFGS \/\//\ MERLIN Description Unber of Calls Olerance Radb-Bound	IS AT DFP - Pane	YOUR COMMAND	
HUNDER OF BFGS CRLLS: 18 /\/\/\/\/\ NERLIN IS AT YOUR CONMAND !!! FP DFP - PANEL INDEX DESCRIPTION UNDER OF CALLS 300 ANY INTEGER 0.100E-02 ANY REAL IN (0,1) 0.100E-01 ANY REAL IN (0,1) 0.100E-01 ANY REAL IN (0,1) 0.100E-01 ANY REAL IN (0,1) 1 HUNDER OF CALLS 300 ANY REAL IN (0,1) 1 HUNDER-BOUND 0.100E-01 ANY REAL IN (0,1) 1 HUNDER-BOUND 0.100E-01 ANY REAL IN (0,1) 1 HUNDER-BOUND 0.100E-01 ANY REAL IN (0,1) 1 HUNDER-BOUND 1 OF CARCEL-BUTTON 1 HUNDER OF DFP CALLS: OF CALLS FIXED 0 HUNDER OF DFP CALLS: OF CALLS SINCE LAST RESET 2271 IN A 0.10050000000000 OF CALLS SINCE LAST RESET 2271 IN A 0.10658140073078-133 J Z 0.106581410073078-135	/\/\/ FP INDEX 1) H 2) T 3) E 4) L 5) U 6) U 6) U 7) H 8) C	UNBER OF BFGS	IS AT DFP - Pane	YOUR COMMAND	
DFP - PAHEL DFP - PAHEL INDEX DESCRIPTION VALUE MEMU 1) HUHBER OF CALLS 300 ANY INTEGER 2) TOLERANCE 0.100E-02 ANY REAL IN (0,1) 3) ERADA-BOUND 0.100E-01 ANY REAL IN (0,1) 4) USE/RECALCULATE GRADIENT 1 (1/0) 5) USE/RECALCULATE GRADIENT 1 (1/0) 6) PRINTOUT SELECTION 1 0/1/2 7) UALL-PARAMETER 3 ANY INTEGER 8) CANCEL-BUTTON 1 (0/1/2) ENTER CHANGES ILL VARIABLES FIXED MUHBER OF DFP CALLS: 0 ////////// NERLIN IS AT YOUR CONMAND 111 :HORTDIS OTAL NU. OF CALLS = 2271 U. OF CALLS SINCE LAST RESET 2271 1) X 3.000000000000 2) Y	FP 	DESCRIPTION Unber of Calls Olerance Rror-Bound	DFP - PANE		
DFP PAHEL INDEX DESCRIPTION VALUE MEHU 1) HUHBER OF CALLS 300 ANY INTEGER 2) TOLERANCE 0.100E-02 ANY REAL IN (0,1) 3) ERBOR-BOUHD 0.100E-01 ANY REAL IN (0,1) 4) USE/RECALCULATE GRADIENT 1 (1/0) 5) USE/RESET HESSIAN 1 (1/0) 6) PRINTOUT SELECTION 1 0/1/2 7) UALL-PARAMETER 3 ANY INTEGER 8) CANCEL-BUTTON 1 (0/1/2) ENTER CHANGES LL VARIABLES FIXED NUMBER OF DFP CALLS: 0 /\/\/\/\/\/\ NERLIN IS AT YOUR CONMAND !!! HORTDIS DTAL NU. OF CALLS = 2271 J. OF CALLS SINCE LAST RESET 2271 1) X 3.00000000000 2) Y	FP IHDEX 1) H 2) T 3) E 4) L 5) U 5) U 6) P 7) H 8) C	DESCRIPTION Unber of Calls Olerance Rror-Bound	DFP - PANE		
DFP - PANEL INDEX DESCRIPTION VALUE MEHU 1) NUMBER OF CALLS 300 ANY INTEGER 2) TOLERANCE 0.100E-02 ANY REAL IN (0,1) 3) ERROR-BOUND 0.100E-01 ANY REAL IN (0,1) 4) USE/RECALCULATE GRADIENT 1 (1/0) 5) USE/RECALCULATE GRADIENT 1 (1/0) 6) PRINTOUT SELECTION 1 0/1/2 7) UALL-PARAMETER 3 ANY INTEGER 8) CANCEL-BUTTON 1 (0/1/2) ENTER CHANGES LL VARIABLES FIXED NUMBER OF DFP CALLS: 0 /////////// NERLIN IS AT YOUR COMMAND III HORTDIS OTAL NU. OF CALLS - 2271 U. OF CALLS SINCE LAST RESET 2271 1) X	IHDEX 1) N 2) T 3) E 4) L 5) U 6) P 7) W 8) C	DESCRIPTION Unber of Calls Oleaance Rag-Bound	DFP - PANE	:L	
INDEX DESCRIPTION VALUE NENU 1) NUMBER OF CALLS 300 ANY INTEGER 2) TOLERANCE 0.100E-02 ANY REAL IN (0,1) 3) ERBOR-BOUND 0.100E-01 ANY REAL IN (0,1) 4) USE/RECALCULATE GRADIENT 1 (1/0) 5) USE/RESET HESSIAN 1 (1/0) 6) PRINTOUT SELECTION 1 0/1/2 7) UALL-PARAMETER 3 ANY INTEGER 8) CANCEL-BUTTON 1 (0/1/2) ENTER CHANGES LL VARIABLES FIXED NUMBER OF DFP CALLS: 0 /////////// NERLIN IS AT YOUR COMMAND III HORTDIS OF CALLS = 2271 U. OF CALLS SINCE LAST RESET 2271 1) X 3.00000000000 2) Y 0.100580410073078-133 3) 3) Z 0.587229414820820-135	IHDEX 1) N 2) T 3) E 4) L 5) U 6) P 7) W 8) C	DESCRIPTION UMBER OF CALLS Olerance RRDA-BOUND		VALUE 300	MENU ANY INTEGER
5) USE/HESEI HESSIAN 1 (1/0) 6) PRINTOUT SELECTION 1 0/1/2 7) UALL-PARAMETER 3 AHY INTEGER 8) CANCEL-BUTTON 1 (0/1/2) ENTER CHANGES ILL VARIABLES FIXED NUMBER OF DFP CALLS: 0 /\/\/\/\/\/ NERLIN IS AT YOUR CONMAND !!! :HORTDIS 0 0 OTAL NU. OF CALLS = 2271 U. OF CALLS SINCE LAST RESET 2271 1) X 3) Z 3) Z	2) T 3) E 4) L 5) U 6) P 7) H 8) C	OLEAANCE Rror-bound		300	ANY INTEGER
5) USE/HESEI HESSIAN 1 (1/0) 6) PRINTOUT SELECTION 1 0/1/2 7) UALL-PARAMETER 3 AHY INTEGER 8) CANCEL-BUTTON 1 (0/1/2) ENTER CHANGES ILL VARIABLES FIXED NUMBER OF DFP CALLS: 0 /\/\/\/\/\/ NERLIN IS AT YOUR CONMAND !!! :HORTDIS 0 0 OTAL NU. OF CALLS = 2271 U. OF CALLS SINCE LAST RESET 2271 1) X 3) Z 3) Z	2) T 3) E 4) L 5) U 6) P 7) H 8) C	OLEAANCE Rror-bound			
5) USE/HESEI HESSIAN 1 (1/0) 6) PRINTOUT SELECTION 1 0/1/2 7) UALL-PARAMETER 3 AHY INTEGER 8) CANCEL-BUTTON 1 (0/1/2) ENTER CHANGES ILL VARIABLES FIXED NUMBER OF DFP CALLS: 0 /\/\/\/\/\/ NERLIN IS AT YOUR CONMAND !!! :HORTDIS 0 0 OTAL NU. OF CALLS = 2271 U. OF CALLS SINCE LAST RESET 2271 1) X 3) Z 3) Z	4) L 5) U 6) P 7) N 8) C	RROR-BOUND		0.100E-02	ANY REAL IN (0,1)
3) USE/MESEL MESSIAN 1 (1/0) 6) PRINTOUT SELECTION 1 0/1/2 7) UALL-PARAMETER 3 AHV INTEGER 8) CANCEL-BUTTON 1 (0/1/2) ENTER CHANGES LL VARIABLES FIXED NUMBER OF DFP CALLS: 0 /\/\/\/\/\/ NERLIN IS AT YOUR CONMAND HORTDIS 0 0 0 OTAL NU. OF CALLS 2271 2271 1. X 3.00000000000 2) Y 0.40658410073078-133 3) Z 0.507229418220820-135	5) U 6) P 7) H 8) C	CE / DCCOL CULOTE COON I		0.100E-01	ANY REAL IN (0,1)
5) USE/HESEI HESSIAN 1 (1/0) 6) PRINTOUT SELECTION 1 0/1/2 7) UALL-PARAMETER 3 AHY INTEGER 8) CANCEL-BUTTON 1 (0/1/2) ENTER CHANGES ILL VARIABLES FIXED NUMBER OF DFP CALLS: 0 /\/\/\/\/\/ NERLIN IS AT YOUR CONMAND !!! :HORTDIS 0 0 OTAL NU. OF CALLS = 2271 U. OF CALLS SINCE LAST RESET 2271 1) X 3) Z 3) Z	5) U 6) P 7) H 8) C	SE/RECRECUENTE ONNOT	EHT	1	(1/0)
7) UALL-PARAMETER 3 ANY INTEGER 8) CANCEL-BUTTON 1 (0/1/2) ENTER CHANGES LL URRIABLES FIXED HUMBER OF DFP CALLS: 0 /\/\/\/\/\/ MERLIN IS AT YOUR COMMAND III HORTDIS 0 0 OTAL NU. OF CALLS 2271 2271 U. OF CALLS SINCE LAST RESET 2271 1) X 3.00000000000 2) Y 0.10658140073078-133 3) Z 0.50722914820820-135	7) U 8) C	SE/RESET HESSIAN		1	(1/0)
8) CANCEL-BUTTOM 1 (0/1/2) ENTER CHANGES ILL VARIABLES FIXED NUMBER OF DFP CALLS: 0 /\/\/\/\/\ NUMBER OF DFP CALLS: 0 /\/\/\/\/\/\ NERLIN IS AT YOUR COMMAND !!! HORTDIS OTALLS = 2271 U. OF CALLS = 2271 1.) X 3.0000000000000 2) Y 0.10658140073078-133 3) Z 0.587229141820820-135	8) C	RINTOUT SELECTION		1	0/1/2
ENTER CHANGES ILL VARIABLES FIXED NUMBER OF DFP CALLS: 0 ////////////////////////////////////		ALL-PARAMETER		3	ANY INTEGER
ENTER CHANGES ILL VARIABLES FIXED HUMBER OF DFP CALLS: 0 ////////////////////////////////////					
HUMBER OF DFP CALLS: O /\/\/\/\/\ MERLIN IS AT YOUR CONMAND III SHORTDIS O 2271 O O O OF CALLS SHOE 2271 O O O 1.0 OF CALLS SHOE 2271 2.) Y 3.000000000000 O 2.) Y 0.40658440073078-133 3) Z	ENTER	CHANGES			
///////// MERLIN IS AT YOUR COMMAND !!! Hortdis Otal NU. Of Calls = 2271 U. Of Calls Since Last Reset 2271 1) X 3.000000000000 2) Y 0.10658440073078-133 3) Z 0.58722944820820-135					
HORTDIS OTAL NU. OF CALLS = 2271 U. OF CALLS SINCE LAST RESET 2271 1) X 3.000000000000 2) Y 0.10658140073078-133 3) Z 0.58722941820820-135	н	UMBER OF DFP	CALLS:	0	
HORTDIS OTAL NU. OF CALLS = 2271 U. OF CALLS SINCE LAST RESET 2271 1) X 3.000000000000 2) Y 0.10658140073078-133 3) Z 0.58722941820820-135					
DTAL NU. OF CALLS = 2271 U. OF CALLS SINCE LAST RESET 2271 1) X 3.000000000000 2) Y 0.10658410073078-133 3) Z 0.58722941820820-135		\/\/\/\ MERLIN	IS AT	YOUR CONNAND	- 111
U. OF CALLS SINCE LAST RESET 2271 1) X 3.00000000000 2) Y 0.10658110073078-133 3) Z 0.58722911820820-135					
1) X 3.000000000000 2) Y 0.40658440073078-133 3) Z 0.58722944820820-135					
2) Y 0.40658440073078-133 3) Z 0.58722944820820-135					
	1-) X				
	2) Y	0.			
VHLUE 0.16838565116755-264					
		VHLUE 0.	168385651	16755-264	